

О продукте

Aksa power generation system, providing optimum performance, and reliability, for stationary standby, prime power, and continuous duty applications. All generator sets are factory build, and production tested.

СЕРТИФИКАТЫ

TS ISO 8528

CE

SZUTEST

2000/14/EC

Общие Характеристики

Название Модели	APD 150 BD
Частота (Гц)	50
вид используемого топлива	Diesel
бренд и модель двигателя	BAUDOUIN - 6M11G150
генератор переменного тока марки и модели	Aksa - AK 4110
Модель панели управления	DSE 6120
кожуха	ACP 6B

Производитель сохраняет за собой право без предварительного уведомления делать изменения в моделях, технических характеристиках, цветах, оборудовании, аксессуарах и чертежах.



3 Количество фаз, 50 Hz, PF 0.8

Напряжение (В)	Мощность Standby		Мощность Prime		Standby Amper
	kVA	kW	kVA	kW	
400/231	150	120.00	138	110.40	216.51

Мощность Standby : Используется при подаче электроэнергии переменной электрической нагрузке в случае прерывания надежного источника сети. ESP совместим с ISO8528. Перегрузка не допускается.

Мощность Prime : Используется для неограниченных рабочих часов ежегодно при подаче электроэнергии переменной электрической нагрузке. PRP совместим с ISO 8528. Согласно ISO3046 в 12-часовой период работы 1 час используется для 10% перегрузки.

двигатель особенность

двигатель		BAUDOUIN
Инженерная модель		6M11G150
Число цилиндров		6 cylinders - in line
Диаметр поршня x Ход поршня	mm	105 X 130
Объем цилиндров	L	6.75
Забор воздуха и охлаждение		Turbo Charged and Air to Air AfterCooled

Производитель сохраняет за собой право без предварительного уведомления делать изменения в моделях, технических характеристиках, цветах, оборудовании, аксессуарах и чертежах.



Степень сжатия		18:1	
скорость	d/dk	1500	
Объем масла в двигателе (включая фильтр) (L)	L	19	
дополнительная мощность		140/188	
Основная мощность		128/172	
Количество подогревателей блока			
		1	
Мощность подогревателя блока			
		1500	
вид используемого топлива			
		Diesel	
Топливная система и тип			
		Direct	
Тип ТНВД			
		Mechanical	



Регулятор частоты вращения двигателя			
		Electronic	
рабочее напряжение			
		12 Vdc	
емкость аккумулятора (Qty/Ah)			
		1x85	
Зарядный генератор			
		80	
Способ охлаждения			
		Water Cooled	
Воздушный поток вентилятора (м3/мин)			
		304.5	
Объем Охлаждающей Жидкости(Только с Двигателем/Радиатором)(л)			
		8/21	
воздушный фильтр			
		Dry Type	



Расход топлива при 100% нагрузке (л/ч)			
		30.2	
Расход топлива при 75% нагрузке (л/ч)			
		23	
Расход топлива при 50% нагрузке (л/ч)			
		15.9	

ТИП АЛЬТЕРНАТОРА

Производитель		Aksa
генератор переменного тока марки и модели		AK 4110
Частота (Гц)	Hz	50
Мощность (кВА)	kVA	137,5
дизайн		Brushless
Напряжение (В)	V	400
фаза		3



Регулятор напряжения		AS460
Система возбуждения	(+/-)	1,5%
Класс изоляции		H
класс защиты		IP22
Активная мощность		0.8
Полный вес генератора (кг.)		492
охлаждающий воздух	m³	30,84

Размеры и вес

Открытый тип	Вес (Нефть и вода нет) (kg.)	длина (mm) (mm.)	ширина (mm) (mm.)	высота (mm) (mm.)	Емкость топливного бака (L.) (Lt.)
	1900	2641	1100	1465	
кожуха	Вес (Нефть и вода нет) (kg.)	длина (mm) (mm.)	ширина (mm) (mm.)	высота (mm) (mm.)	Емкость топливного бака (L.) (Lt.)



ACP 6B Image not found of type unknown 	2380	3265	1163	1858	271
--	------	------	------	------	-----

стандартные функции

Water cooled, Diesel engine
Radiator with mechanical fan
Protective grille for rotating and hot parts
Electric starter and charge alternator
Starting battery (with lead acid) including rack and cables
Engine coolant heater
Base frame design incorporates an integral fuel tank and anti-vibration isolators
Flexible fuel connection hoses
Single bearing, class H alternator
Industrial exhaust silencer and steel bellows supplied separately (for open sets)
Static battery charger
Manual for application and installation

Оборудование на Заказ

ENGINE

- Fuel-Water Separator Filter
- Oil heater

ALTERNATOR

- Anti-Condensation Heater
- Over sized alternator
- PMG excitation + AVR
- Main line circuit breaker

CONTROL SYSTEM

- Automatic synchronising and power control system (multi gen-set Parallel)
- Transition synchronization with mains
- Remote annunciator panel
- Remote relay output
- Alarm output relays
- Remote communication with modem

Производитель сохраняет за собой право без предварительного уведомления делать изменения в моделях, технических характеристиках, цветах, оборудовании, аксессуарах и чертежах.



- Earth fault, single set
- Charge Ammeter

TRANSFER SWITCH

- Three Pole Contactor
- Four Pole Contactor
- Three or four pole motor operated circuit breaker

OTHER ACCESSORIES

- Main Fuel Tank
- Automatic or manual fuel filling system
- Manual oil drain pump
- Electrical oil drain pump
- Low and high fuel level alarm
- Residential silencer
- Enclosure: weater protective or sound attenuated
- Duct adapter (on radiator)
- Inlet and outlet motorised louvers
- Inlet and outlet acoustic baffles
- Trailer
- Tool kit for maintenance
- Automatic transfer switch

Приборы

- DSE, model 6120 Auto Mains Failure control module.
- Battery charger input 198-264 volt, output 27,6 V 5 A (24 V) or 13,8 Volt 5A (12V)
- Emergency stop push button and fuses for control circuits.

Строительство и завершение

- Components installed in sheet steel enclosure. Phosphate chemical, pre-coating of steel provides corrosion resistant surface. Polyester composite powder topcoat forms high gloss and extremely durable finish. Lockable and hinged panel door provides easy access to components.

Установка

Control panel is mounted on baseframe with steel stand. Located at the right side of the generator set (When you look at the Gen.Set. from Alternator)

Блок управления генератором



The DSE 6120 module has been designed to monitor generator frequency, volt, current, engine oil pressure, coolant temperature running hours and battery volts.

Module monitors the mains supply and switch over to the generator when the mains power fails.

The DSE6120 also indicates operational status and fault conditions, Automatically shutting down the Gen.

Set and giving true first up fault condition of Gen. Set failure. The LCD display indicates the fault.

Стандартные функции

- Microprocessor controlled.
- LCD display makes information easy to read.
- Automatically transfers between mains (utility) and generator power.
- Manual programming on front panel.
- User-friendly set-up and button layout.
- Remote start.
- Event logging (50) showing date and time.
- Controls: Stop/Reset, Manual, Auto, Test, Start, buttons. An additional push button next to the LCD display is used to scroll through the modules' metering displays.

Измерительные приборы

ENGINE

- Engine speed.
- Oil pressure.
- Coolant temperature.
- Run time.
- Battery volts.
- Configurable timing.

GENERATOR

- Voltage (L-L, L-N).
- Current (L1-L2-L3).
- Frequency.
- Gen. Set ready.
- Gen. Set enabled.

MAINS

- Mains ready.
- Mains enabled.

Схема защиты

WARNING

- Charge failure.
- Battery Low/High voltage.
- Fail to stop.
- Low /High generator voltage.



- Under /Over generator frequency.
- Over /Under speed.
- Low oil pressure.
- High coolant temperature.

SHUT DOWNS

- Fail to start.
- Emergency stop.
- Low oil pressure.
- High coolant temperature.
- Over /Under speed.
- Under/over generator frequency.
- Under/over generator voltage.
- Oil pressure sensor open.
- Coolant temperature sensor open.

ELECTRICAL TRIP

- Generator over current.

Опционные особенности

- Flexible sensor can be controlled with temperature, pressure, percentage (warning/shutdown/electrical trip)
- Local setting parameters and monitoring from PC to control module with USB connection (max 6 mt).

Стандарты

- Electrical Safety / EMC compatibility
- BS EN 60950 Electrical business equipment.
- BS EN 61000-6-2 EMC immunity standard.
- BS EN 61000-6-4 EMC emission standard

Статический аккумулятор Выпрямитель (зарядное устройство)

- Battery charger is manufactured with switching-mode and SMD technology and it has high efficiency.
- Battery charger models' output V-I characteristic is very close to square and output is 5 amper, 13,8 V for 12 volt and 27,6 V for 24 V . Input 198 - 264 volt AC.
- The charger is fitted with a protection diode across the output.
- Connect charge fail relay coil between positive output and CF output.
- They are equipped with RFI filter to reduce electrical noise radiated from the device.
- Galvanically isolated input and output typically 4kV for high reliability.

О продукте

Звукоизоляционные и всепогодные кожухи для генераторных установок Akса отвечают требованиям по шумоизоляции и обеспечивают оптимальную защиту от неблагоприятных погодных условий и разработаны нашими инженерами-акустиками.

Наши звукоизолированные контейнеры модульной конструкции обеспечивают легкий доступ для сервисного обслуживания, а также легкую взаимозаменяемость компонентов, позволяющую производить ремонт на объекте.

Кожухи и контейнеры предназначены для оптимизации характеристик охлаждения генераторной установки, обеспечивая уверенность в номинальных характеристиках генераторной установки.

стандартные функции

Серийная модель кожуха		ACP 6A
ширина (mm)	mm.	1058
длина (mm)	mm.	2600
высота (mm)	mm.	1590
Емкость топливного бака (L.)	Lt.	180