



## FEATURES

### FUEL GAUGE

Fuel gauge is on the fuel tank

### OHV

Over Head Valve easy to maintenance

### OIL LEVEL ALARM

When the oil level is low that the engine will not start. voltage of a generator.

### AVR

AVR is a device often solid state, for controlling the output

### CIRCUIT PROTECTOR

Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.

### LED DISPLAY

LED screen to monitor voltage and current with hourmeter

### CHOKE SYSTEM

When the cold weather, choke system aid to operate the engine.

### DUAL ELEMENT AIR FILTER

### LARGE CAPACITY FUEL TANK

15-25lt

-Z μ v Ÿ u u Ç À Æ Ç % v ] v P } v ( μ o š v l % ] š Ç •

## GENERAL SPECIFICATIONS

3 Phase, 50 Hz, PF 0.8

AC Rated Power	kVA(kW)	1 3 (1 0 ,4 )
Maximum Power	kVA(kW)	1 4 ,5 (1 1 ,6)
AC Nominal Current (A)		20 ,9
Voltage (V)		230/400
Frequency (Hz)		
Phase Number		
Power Factor		
Fuel Consumption %100 (lt/h)		7,5
Fuel Consumption %75 (lt/h)		6,12
Fuel Consumption %50 (lt/h)		4,6
Noise Level (dB(A))		78,8

Manufacturer reserves the right to make change in the model, technical specifications, color, equipment, accessories and images without prior notice.

(19.07.2017)



## ENGINE SPECIFICATIONS

Speed (Rpm)	36 00
Power (Hp)	23
Fuel Type	Gasoline
Oil Capacity (L.)	1,7
Fuel Tank Capacity (L.)	16
Starting System	Electric/Manual

## DIMENSIONS AND WEIGHT

Width (mm.)	740
Lenght (mm.)	910
Height (mm.)	750
Dry Weight (kg.)	160