INTRODUCTION

Aksa power generation system, providing optimum performance, and reliability, for stationary standby applications. All generator sets are factory build, and production tested.

Certificate

TS ISO 8528

TS ISO 9001-2008

CE

SZUTEST

2000/14/EC

General Characteristics

Model Name	APD 200 A
Frequency (Hz)	50
Fuel Type	Diesel
Engine Made and Model	AKSA - A6CRX71TI
Alternator Made and Model	Aksa - AK 4150
Control Panel Model	DSE 6120
Canopy	ACP 6B

Производитель сохраняет за собой право без предварительного уведомления делать изменения в моделях, технических характеристиках, цветах, оборудовании, аксессуарах и чертежах.

3 Phase, 50 Hz, PF 0.8

VOLTAGE	STANDBY RATING (ESP)		PRIME RATING (PRP)		Standby Amper
	kVA	kW	kVA	kW	
400/231	200	160.00	182	145.60	288.68

STANDBY RATING (ESP) : Applicable for supplying power to varying electrical load for the duration of power interruption of a reliable utility source. ESP is in accordance with ISO 8528-1. Overload is not allowed.

PRIME RATING (PRP) : Applicable for supplying power to varying electrical load for unlimited hours. PRP is in accordance with ISO 8528-1. 10 % overload capability is available for a period of 1 hour within 12-hour perod of operation.

ENGINE SPECIFICATIONS

Engine		AKSA
Engine Model		A6CRX71TI
NO. OF CYLINDERS AND BUILD		6 cylinders - in line
BORE AND STROKE	**mm**	110 X 125
TOTAL DISPLACEMENT	**L**	7.13
Aspiration		Turbo Charged and Intercooled(Water to Air)

Производитель сохраняет за собой право без предварительного уведомления делать изменения в моделях, технических характеристиках, цветах, оборудовании, аксессуарах и чертежах.

COMPRESSION RATIO		17:1
RATED SPEED (RPM)	**d/dk**	1500
OIL CAPACITY	**L**	16
Standby Power (kW/HP)		182/247.45
Prime Power		166/225.7
Block Heater QTY		1
Block Heater Power (Watt)		1500
Fuel Type		Diesel
Injection Type and System		Direct
Type of Fuel Pump		P pump

Производитель сохраняет за собой право без предварительного уведомления делать изменения в моделях, технических характеристиках, цветах, оборудовании, аксессуарах и чертежах.

Governor System		Electronic
Operating Voltage (Vdc)		24 Vdc
Battery and Capacity (Qty/Ah)		2x80
Cooling Method		Water Cooled
Cooling Fan Air Flow (m3/min)		190
Coolant Capacity (engine only / with radiator) (lt)		9,55/38
Air Filter		Dry Type
Fuel Cons. Prime With %100 Load (lt/hr)		42.5

Производитель сохраняет за собой право без предварительного уведомления делать изменения в моделях, технических характеристиках, цветах, оборудовании, аксессуарах и чертежах.

ALTERNATOR SPECIFICATIONS

Manufacturer		Aksa
Alternator Made and Model		AK 4150
Frequency (Hz)	**Hz**	50
Power (kVA)	**kVA**	187.5
DESIGN		Brushless
VOLTAGE	**V**	400
Phase		3
A.V.R.		SX440
Voltage Regulation	**(+/-)**	1%
Insulation System		H
Protection		IP22
Rated Power Factor		0.8
WEIGHT COMP. GENERATOR (Kg)		580

Производитель сохраняет за собой право без предварительного уведомления делать изменения в моделях, технических характеристиках, цветах, оборудовании, аксессуарах и чертежах.

COOLING AIR (m³/min)	**m^3**	30,84

SIZE and WEIGHT

Open Type	**DRY WEIGHT (kg.) (kg.)**	**LENGTH (mm.)**	**WIDTH (mm.)**	**HEIGHT (mm.)**	**TANK CAPACITY (lt.) (Lt.)**
	-	-	-	-	
CANOPY	**DRY WEIGHT (kg.) (kg.)**	**LENGTH (mm.)**	**WIDTH (mm.)**	**HEIGHT (mm.)**	**TANK CAPACITY (lt.) (Lt.)**
ACP 6B Image not found or type unknown	2180	3265	1163	1858	271

STANDART SPECIFICATIONS

Water cooled, Diesel engine
Radiator with mechanical fan
Protective grille for rotating and hot parts
Electric starter and charge alternator
Starting battery (with lead acid) including rack and cables
Engine coolant heater
Base frame design incorporates an integral fuel tank and anti-vibration isolators
Flexible fuel connection hoses
Single bearing, class H alternator
Industrial exhaust silencer and steel bellows supplied separately(for open sets)
Static battery charger
Manual for application and installation

Производитель сохраняет за собой право без предварительного уведомления делать изменения в моделях, технических характеристиках, цветах, оборудовании, аксессуарах и чертежах.

OPTIONAL EQUIPMENTS

ENGINE

- Fuel-Water Seperator Filter
- Low water level alarm
- Oil heater

ALTERNATOR

- Anti-Condensation Heater
- Main line circuit breaker

CONTROL SYSTEM

- Earth fault, single set
- Charge Ammeter

TRANSFER SWITCH

- Three Pole Contactor
- Four Pole Contactor
- Three or four pole motor operated circuit breaker

OTHER ACCESSORIES

- Main Fuel Tank

Производитель сохраняет за собой право без предварительного уведомления делать изменения в моделях, технических характеристиках, цветах, оборудовании, аксессуарах и чертежах.

- Automatic or manual fuel filling system
- Manual oil drain pump
- Low and high fuel level alarm
- Enclosure: weater protective or sound attenuated
- Trailer
- Tool kit for maintenance

Devices

● DSE, model 6120 Auto Mains Failure control module.
● Battery charger input 198-264 volt, output 27,6 V 5 A (24 V) or 13,8 Volt 5A (12V)
● Emergency stop push button and fuses for control circuits.

Construction and finish

● Components installed in sheet steel enclosure. Phosphate chemical, pre-coating of steel provides corrosion resistant surface. Polyester composite powder topcoat forms high gloss and extremely durable finish. Lockable and hinged panel door provides easy access to components.

Installation

Control panel is mounted on baseframe with steel stand. Located at the right side of the generator set (When you look at the Gen.Set. from Alternator)

GENERATING SET CONTROL UNIT

The DSE 6120 module has been designed to monitor generator frequency, volt, current, engine oil pressure, coolant temperature running hours and battery volts.
Module monitors the mains supply and switch over to the generator when the mains power fails.
The DSE6120 also indicates operational status and fault conditions, Automatically shutting down the Gen. Set and giving true first up fault condition of Gen. Set failure.The LCD display indicates the fault.

Производитель сохраняет за собой право без предварительного уведомления делать изменения в моделях, технических характеристиках, цветах, оборудовании, аксессуарах и чертежах.

Стандартные функции

- Microprocessor controlled.
- LCD display makes information easy to read.
- Automatically transfers between mains (utilty) and generator power.
- Manual programming on front panel.
- User-friendly set-up and button layout.
- Remote start.
- Event logging (50) showing date and time.
- Controls: Stop/Reset, Manual, Auto, Test, Start, buttons. An additional push button next to the LCD display is used to scroll through the modules' metering displays.

Измерительные приборы

ENGINE

- Engine speed.
- Oil pressure.
- Coolant temperature.
- Run time.
- Battery volts.
- Configurable timing.

GENERATOR

- Voltage (L-L, L-N).
- Current (L1-L2-L3).
- Frequency.
- Gen. Set ready.
- Gen. Set enabled.

MAINS

- Mains ready.
- Mains enabled.

Схема защиты

WARNING

- Charge failure.
- Battery Low/High voltage.
- Fail to stop.
- Low /High generator voltage.
- Under /Over generator frequency.
- Over /Under speed.
- Low oil pressure.
- High coolant temperature.

SHUT DOWNS

- Fail to start.

Производитель сохраняет за собой право без предварительного уведомления делать изменения в моделях, технических характеристиках, цветах, оборудовании, аксессуарах и чертежах.

- Emergency stop.
- Low oil pressure.
- High coolant temperature.
- Over /Under speed.
- Under/over generator frequency.
- Under/over generator voltage.
- Oil pressure sensor open.
- Coolant temperature sensor open.

ELECTRICAL TRIP

- Generator over current.

Опционные особенности

- Flexible sensor can be controlled with temperature, pressure, percentage (warning/shutdown/electrical trip)
- Local setting parameters and monitoring from PC to control module with USB connection (max 6 mt).

Стандарты

- Elecrical Safety / EMC compatibility
- BS EN 60950 Electrical business equipment.
- BS EN 61000-6-2 EMC immunity standard.
- BS EN 61000-6-4 EMC emission standard.

STATIC BATTERY CHARGER

- Battery charger is manufactured with switching-mode and SMD technology and ıt has high efficiency.
- Battery charger models' output V-I characteristic is very close to square and output is 5 amper, 13,8 V for 12 volt and 27,6 V for 24 V . Input 198 - 264 volt AC.
- The charger is fitted with a protection diode across the output.
- Connect charge fail relay coil between positive output and CF output.
- They are equipped with RFI filter to reduce electrical noise radiated from the device.
- Galvanically isolated input and output typically 4kV for high reliability.

Производитель сохраняет за собой право без предварительного уведомления делать изменения в моделях, технических характеристиках, цветах, оборудовании, аксессуарах и чертежах.